

RE716P1TLP(G) Manual Pull Station



Product Overview

RE-716P Manual Pull Station is a high quality non-toxic die-cast manual pull station. Low profile design and smooth edges offer an attractive yet functional design. All components are prepainted or have plated surfaces to inhibit corrosion. Electrically the RE-716P Manual pull station is unbeatable with 10 Amp snap action switch offered in all possible contact arrangements (including gold contacts). The RE-716P pull station can be used with or without a break glass rod with replacement requiring no special tools.

Features

- Lift and pull
- Break glass cover
- Weather and Explosion proof versions
- All stations offer hex screw or key lock access.

Construction Material

- Painted Die Cast Housing.
- 14 Ga plated steel black plate.
- Corrosion inhibited surfaces.
- Terminal block (4 Position)
- Single Gang Mounting
- 10 A , 120VAC snap action switch (S.P.S.T.)



Specification

Electrical

Switch : 10A@120VAC

Dimensions

Station Width : 3.200 in
Length : 4.750 in
Depth : 0.875 in
Weight : 15.5 oz / 420 grams
Mount : Single gang

Ordering Information

MODELS	DESCRIPTION	COLOR
RE716P1TLP(G)	Manual Pull station Dual Action	GREEN



India:

RAVEL ELECTRONICS PVT LTD.,
(An ISO 9001 Certified Company)
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.
E-Mail: marketing@ravelfire.com; Web : www.ravelfire.com

United Kingdom:

RAVEL ELECTRONICS LTD.,
Unit 11, Chancel Industrial Estate, Newhall street,
Willenhall WV13 1NX, West Midlands, United Kingdom.
E-mail: info@ravelfire.co.uk ;Web: www.ravelfire.co.uk